



BLUETOOTH SWITCH IT-BT



D Bedienungsanleitung
F Mode d'emploi
E Manual de instrucciones
P Instruções de funcionamento
TR İşletme talimatı
SK Návod na obsluhu
SLO Navodilo za uporabo
R Руководство по обслуживанию
RO Manual de utilizare
FIN Käyttöohje
NL Gebruiksaanwijzing
N Bruksanvisning

GB Operating Instructions
I Istruzioni d'uso
EST Kasutusjuhend
GR Οδηγίες χρήσης
H Kezelési utasítás
CZ Návod k obsluze
PL Instrukcja obsługi
S Bruksanvisning
BG Ръководство за обслужване
HR Uputa za rukovanje
DK Betjeningsvejledning
IS Notkunarleiðbeiningar

With the Bluetooth IT-BT switch, the Android smartphone becomes your control centre for all intertechno radio-controlled receivers (from 1995) indoors and outdoors.

Preparing the BT switch (Fig. 1).

1. The battery (type CR 2032) for the timer function is already inserted upon delivery.
2. Connect the BT switch using the enclosed power supply unit.
The device is ready for use when the blue LED lights up.

Operating the BT switch:

1. Download the free Android app under the QR code (Fig. 2) and install the app.
As an alternative, search for "intertechno BT switch" in the Android market.
2. The Android app automatically searches for the BT switch.
This may take up to 40 seconds. Confirm the pairing query (Fig. 3).
3. Successful connection is confirmed by a message.
The connection remains active as long as the smartphone remains within the range of the BT switch, even if the app is not active.
Up to 6 smartphones can be connected at the same time with the BT switch.



Adding and encoding modules (IT receivers):

- 1.) Self-learning radio-controlled receivers:
In order to provide more security for all self-learning radio-controlled receivers from intertechno, a secure password for the password codes is determined under Settings (⚙️).
Confirm via "Save".
- 2.) A new radio-controlled receiver is determined by clicking on the symbol "Add module" (🏠).
1.) Enter name (e.g. garden pump).
2.) Select the corresponding module.
3.) Selection of coding.
The encoding wheel codes from A-P and 1-16 are available.
Any number of passwords can be chosen in the password codes, whereby up to 16 self-learning IT receivers can be switched under each password.
Finish via "Save".

TIMER

The symbol "Add timer" (🕒) is pressed for automatic timing.

- 1.) Selection of the module
- 2.) Enter a timer name (e.g. evening watering).
- 3.) Adjusting the times for switching on and off.
The option of only switching either on or off is also possible.
- 4.) Random timing: Selection whether the timer is to begin at random
i.e. switching takes place at the most 15 minutes earlier or later than the actually set time.
- 5.) Repeat: Selection of weekly repetition.
- 6.) Selection of days for switching.

All timer settings are programmed to the BT switch via the function "Program timer".

The status LED briefly lights up green to confirm.

The timers have not been programmed for the BT switch until "Synchronise" has been pressed. The time on the smartphone is used as the time for the timer and is transmitted again for each synchronisation process.

The timer setting is saved by the CR2032 battery, even if the BT switch is switched off.

If no battery is inserted, or if the battery does not have sufficient power, a warning appears in the app at one minute intervals.

Operating information

- Pressing and holding an entry enables you to "Edit" and "Delete" it.
- Pressing and holding the icon of an entry enables you to move the entry.
e.g.: Radio-controlled connecting adapters in front of radio-controlled built-in switches

Icon overview:

